

AC/DC Converter FA5-220SXXY2D4 Series



Typical Features

◆Wide Input Voltage Range: 90-265VAC/127-375VDC

◆No load power consumption≤0.3W

◆Transfer Efficiency: 82% (typ.)

◆Switching Frequency: 65KHz

◆Protections: Short-circuit, Over-current, Over-temperature

◆Isolation voltage: 4000Vac

◆Meet IEC62368/UL62368/EN62368 test standard

◆Conform to CE, RoHS

◆Plastic Case , meet UL94 V-0

◆PCB Mounting



Application Field

FA5-220SXXY2D4 Series-----a compact size, high efficient, meet CE standard power converter offered by Aipu. It features universal input voltage range, AC and DC dual-use, low ripple, low temperature rise, low power consumption, high efficiency, high reliability, safer isolation, with good EMC performance, meet EN55032, IEC/EN61000 standard. The series widely used for power, industry, instrument, smart home application, ect. The application circuit in the datasheet is strongly recommended for harsh EMC environment.

Typical Product List

Certificate	Part No	Oı	ıtput Specificat	ion	Max.	Ripple&	Efficiency@
		Power	Voltage 1	Current 1	Capacitive Load	Noise 20MHz (MAX)	Full Load, 220Vac (Typical)
		(W)	Vo1 (V)	lo1 (m A)	uF	mVp-p	%
	FA5-220S3V3Y2D4	4.1	3.3	1250	2000	80	69
	FA5-220S05Y2D4	5	5	1000	1000	80	71
	FA5-220S09Y2D4	5	9	556	470	120	74
-	FA5-220S12Y2D4	5	12	416	100	120	78
	FA5-220S15Y2D4	5	15	333	100	120	78
	FA5-220S24Y2D4	5	24	208	100	120	79

Note 1: The typical output efficiency is based on that product is full loaded and burned-in after half an hour.

Note 2: The fluctuation range of full load efficiency(%,TYP) is ±2%, full load output efficiency= total output power/module's input power.

Note 3: -T is chassis mounting, -TS is din-rail mounting, din-rail width 35mm.

Input Specifications

input opcomount one								
Item	Operating Condition	Min.	Тур.	Max.	Unit			
Input Voltage Range	AC Input	90	220	265	VAC			
	DC Input	127	310	375	VDC			



AC/DC Converter FA5-220SXXY2D4 Series



Input Frequency Range	-	47	50	63	Hz	
10.10.001	115VAC	1	1	0.10		
Input Current	220VAC	1	1	0.06	Α	
Surga Current	115VAC	-	-	10	A	
Surge Current	220VAC	-	1	20		
Leakage Current	-	0.5mA TYP/230VAC/50Hz				
External Fuse Recommend Value	-	1A-3A/250VAC slow-fusing				
Hot Plug	-	Unavailable				
Remote Control Terminal	-	Unavailable				

Item		Operating Condition	Min.	Тур.	Max.	Unit	
Voltage Accuracy		Full input voltage range, 10%-100% load	-	±2.0	±5.0	%	
Line Regulation		Nominal Load	-	±1.0	±3.0	%	
Load Re	egulation	Nominal input voltage,20%~100% load	-	±1.0	±3.0	%	
No Loa	d Power	Input 115VAC	-	-	0.0	10/	
Consu	ımption	Input 220VAC	-	- 0.3		W	
Minimu	ım Load	Single Output	10	-	-	%	
Turn-on Delay Time		Nominal input voltage (full load)	-	600	-	mS	
Power-off Holding Time		Input 115VAC (full load)	-	100	-		
		Input 220VAC (full load)	-	80	n	mS	
Dynamic	Overshoot range	25%~50%~25%	-5.0	-	+5.0	%	
Response	Recovery time	50%~75%~50%	-5.0	-	+5.0	mS	
Output C	ver-shoot	E 11:00 1 11:00 10:00	≤10%Vo			%	
Short circu	it protection	Full input voltage range	Continuous, Self-recovery			Hiccup	
Drift Coefficient		-	-	±0.03%	-	%/℃	
Over Curre	nt Protection	Input 220VAC	≥120% lo Self-recovery		Hiccup		
		Output Vo≤5VDC	-	40	80		
Ripple & Noise		Output Vo>5VDC	_	60	120	mV	

Note: Ripple& Noise is tested by Twisted Pair Method, details please see Ripple& Noise Test at back.

General Specifications								
Items	Operating Conditions	Min.	Тур.	Max.	Unit			
Switching Frequency	-	-	65	-	KHz			




AC/DC Converter FA5-220SXXY2D4 Series




Operating Temperature		-	-40	-	+75	°C	
Storage Temperature		-	-40	-	+85		
		Wave-soldering	260±4℃, timing 5-10S				
Soldering I	emperature	Manual-soldering	360±8℃, timing 4-7S				
Relative	Humidity	-	10	-	90	%RH	
Isolation Voltage	Input-Outp ut	Test 1min, leakage current≤5mA	4000	-		VAC	
Insulation Resistance	Input-Outp ut	@DC500V	100	-		ΜΩ	
Safety S	Standard	-	EN60950, IEC60950				
Vibra	ation	-	10-55Hz,10G,30Min,alongX,Y,Z				
Safety Class		-	CLASSII				
Class of Case Material		-	UL94 V-0				
MTBF		-	MIL-HDBK-217F@25°C>300,000H				

EMC (EMC Characteristics								
	Total Item	Sub Item	Test Standard	Class					
	EN41	CE	CISPR22/EN55032	CLASS B					
	EMI	RE	CISPR22/EN55032	CLASS B					
		RS	IEC/EN61000-4-3	10V/m Perf.Criteria B (see recommended circuit Photo 1)					
EMC		CS	IEC/EN61000-4-6	3Vr.m.s Perf.Criteria B (see recommended circuit 1)					
	EMS	ESD	IEC/EN61000-4-2	Contact ±6KV / Air ±8KV Perf.Criteria B					
		Surge	IEC/EN61000-4-5	line to line ±2KV / line to ground ±4KV Perf.Criteria B (see recommend circuit 1)					
		EFT	IEC/EN61000-4-4	±2KV Perf.Criteria B					
		Voltage dips and interruptions	IEC/EN61000-4-11	0%~70% Perf.Criteria B					

Y2 Packing Dimension





Pin Definition




AC/DC Converter FA5-220SXXY2D4 Series




Pin-out	1	2	3	4
Single(S)	AC(L)	AC(N)	+Vo	-Vo

Y2-T Packing Dimension



Y2-TS Packing Dimension





AC/DC Converter FA5-220SXXY2D4 Series




Ripple& Noise Test: (Twisted Pair Method 20MHZ bandwidth)


Test Method:


(1) 12# twisted pair to connect, Oscilloscope bandwidth set as 20MHz, 100M bandwidth probe, terminated with 0.1uF polypropylene capacitor and 10uF high frequency low resistance electrolytic capacitor in parallel, oscilloscope set as Sample pattern.

(2) Input terminal connect to power supply, output terminal connect to electronic load through jig plate, Use 30cm±2 cm sampling line, Power line selected from corresponding diameter wire with insulation according to the flow of output current.



Product Characteristic Curve






Note1: Input Voltage should be derated base on Input Voltage Derating Curve when it is 90~120VAC/240~265VAC/ 127~170VDC/340~380VDC Note 2: Our product is suitable to use under natural air cooling environment, if use it under closed condition, please contact with us.

Typical EMC Recommended Application Circuit

1. Recommended Circuit:



Note:

- 1. FUSE: necessary, suggest 2A~250Vac, slow fusing, block form;
- 2. MOV is voltage dependent resistor, suggest model: 10D561K;
- 3. LCM is common mode inductance, recommended value above 30mH; CX1 is X Capacitor, recommended value: 0.22uF/275V;
- 4. NTC1 is thermistors, suggest model:5D-11, to prevent the module from damage when lighting surge.
- 5. C1 is high frequency low impedance electrolytic capacitor whose capacitance value less than capacitive load, withstand voltage is above 1.5 times or more of output voltage.
- 6. C2 is 0.1uF ceramic chip capacitors, withstand voltage is 1.5 times more than output voltage.



AC/DC Converter FA5-220SXXY2D4 Series



7. TVS1 is TVS tube:

5V output recommend: SMBJ7.0A, 9V output recommend:SMBJ12.0A, 12V output recommend:SMBJ20A, 15V output recommend: SMBJ20.0A, 24V output recommend: SMBJ30.0A, 48V output recommend: SMBJ64A.

Note:

- 1. The product should be used under the specification range, otherwise it will cause permanent damage to it.
- 2. Product's input terminal should connect to fuse;
- 3.If the product is not worked under the load range(below the minimum load or beyond the load range), we cannot ensure that the performance of product is in accordance with all the indexes in this manual;
- 4.Unless otherwise specified, data in this datasheet are tested under conditions of Ta=25°C, humidity<75% when inputting nominal voltage and outputting rated load(pure resistance load);
- 5.All index testing methods in this datasheet are based on our Company's corporate standards
- 6.The performance indexes of the product models listed in this manual are as above, but some indexes of non-standard model products will exceed the above-mentioned requirements, please directly contact our technician for specific information;
- 7. We can provide customized product service;
- 8. The product specification may be changed at any time without prior notice.

Guangzhou Aipu Electron Technology Co., Ltd

Address: Building 4, HEDY Park, No.63, Punan Road, Huangpu Dist, Guangzhou, China.

Tel: 86-20-84206763 Fax: 86-20-84206762 HOTLINE: 400-889-8821 E-mail: sales@aipu-elec.com Website: https://www.aipupower.com